
PRODUCT	: LCD MODULE
MODEL NO	: YTCA10TLAK-04-100N
SUPPLIER	: Yes Optoelectronics Co.,Ltd
DATE	: Dec.24.2020

SPECIFICATION

Prepared by	Checked	Approved
LIUJUN	SHIJIN	XIAOYU

CUSTOMER:
MODEL NO.:

DATE:

Approved	Checked	Department

ADD: No.288 Yueling Road Anshan, Liaoning, CHINA
TEL: 86-412-5211859 FAX: 86-412-5211729 P.C.:114045
E-mail : yes@yes-lcd.com, yeslcd@globalsources.com
Web: <http://www.yes-lcd.com>
<http://www.asiansources.com/sante.com>

CONTENTS

1. General Specifications.....	4
2. Mechanical Drawing.....	5
3. PIN Assignment.....	6
4. Absolute Maximum Rating.....	7
5. Electrical Characteristics.....	7
5.1. Recommended Operating Condition.....	7
5.2. Recommended Driving Condition for Backlight.....	7
6. Timing Characteristics.....	8
6.1. AC Electrical Characteristics.....	8
6.2.DC Electrical Characteristics.....	9
6.3.Timing.....	10
6.4.Data input format.....	11
6.5.Power ON/OFF Sequence.....	12
7. Optical Characteristics.....	14
8. Environmental/Reliability Test.....	17
9. Packing Drawing.....	18
10. Standard Specifications For Product Quality.....	18
10.1. Manner of test:.....	19
10.2. Quality specification.....	19
10.3. Definition of area.....	19
10.4. Standard of appearance.....	20
11. Precautions for Use of LCD Modules.....	22
11.1. Handing Precautions.....	22
11.2. Storage Precautions.....	23
11.3. Others.....	23
11.4. USING LCD MODULES.....	23
11.5. The disposal of waste.....	25
12. Prior Consult Matter.....	25
13. Factory.....	25

Revision Record

Rev No.	Rev Date	Contents	Remarks
1.0	2020.12.24	New creation	

1. General Specifications

No.	Item	Contents	Unit
1	Size	10.1	inch
2	Resolution	1024RGB*600	
3	Interface	LVDS	
4	Color Depth	16.7	M
5	Technology Type	a-Si	
6	Pixel Pitch	0.0725*0.2088	mm
7	Pixel Arrangement	R.G.B Vertical Stripe	
8	Display Mode	Normally Black, Transmissive	
9	Viewing Direction	ALL	
10	LCM (W x H x D)	235*143*5.7	mm
11	Active Area (W x H)	222.72*125.28	mm
12	With/Without TSP	Without CTP	

2.Mechanical Drawing

CUSTOMER'S APPROVED:		DATE:		PAGE:	
NO.	DESCRIPTION	DATE			
1	Modify panel backlight and PPC based on YTCA10TLAB-04-100N	2020.12.24			
2					
3					
4					

1 Operating Voltage: VDD=3.3V typ. VLED=5.0V typ. 2 Resolution: 1024RGB*600 3 Color: 16.7M 4 Interface: LVDS 5 Display type: Transmissive,NB 6 Viewing Direction: ALL 7 Operating Temp: -20°C~70°C 8 Storage Temp: -30°C~80°C 9 Driver IC: HX8282-AKH8696-A 10 Surface luminance: 370cd/m2(tp) 11 Unspecified tolerance: ±0.3	1 UPDN 16 Rpin2- 2 SHLR 17 Rpin2+ 3 RESPT 18 GND 4 STBYB 19 Rpin3- 5 VDD 20 Rpin3+ 6 GND 21 GND 7 RactClkIn+ 22 HSD 8 RactClkIn+ 23 VLED 9 GND 24 PWM 10 Rpin0- 25 NC 11 Rpin0+ 26 NC 12 GND 27 NC 13 Rpin1- 28 NC 14 Rpin1+ 29 NC 15 GND 30 NC
--	--

No.YTCA10TLAK-04-100N

Ver.1

Unit:mm

Apv

Yes Optoelectronics Co., Ltd.

Drw 刘璐 2020.12.24

3. PIN Assignment

Pin No.	Symbol	I/O	Function	Remark						
1	UPDN	I	Gate Driver Up/down scan setting. Normally pull low. When UPDN=H, reverse scan. STV1 output vertical start pulse and UD pin output “H” to Gate driver When UPDN=L, normal scan. (Default) STV2 output vertical start pulse and UD pin output “L” to Gate driver.							
2	SHLR	I	Source Driver internal shift register is controlled by this pin as shown below: Normally pull high. SHLR=H: SO1-SO2-SO3 . . . SO1536. (Default) SHLR=L: SO1536-SO1535-SO1534 . . . SO1.							
3	RESET	I	Reset signal							
4	STBYB	I	Standby mode control. Normally pull High. When STB=H, all the functions are on. (Default pulls high) When STB=L, TCON and source driver are off and all output are GND.							
5	VDD	P	Digital power							
6	GND	P	Ground							
7	RxCIn-	I	-LVDS differential clock input							
8	RxCIn+	I	+LVDS differential clock input							
9	GND	P	Ground							
10	Rxin0-	I	-LVDS differential data input							
11	Rxin0+	I	+LVDS differential data input							
12	GND	P	Ground							
13	Rxin1-	I	-LVDS differential data input							
14	Rxin1+	I	+LVDS differential data input							
15	GND	P	Ground							
16	Rxin2-	I	-LVDS differential data input							
17	Rxin2+	I	+LVDS differential data input							
18	GND	P	Ground							
19	Rxin3-	I	-LVDS differential data input							
20	Rxin3+	I	+LVDS differential data input							
21	GND	P	Ground							
22	HSD	I	In LVDS mode, used as 6-bit/8-bit input select. <table><tr><th>HSD</th><th>bit</th></tr><tr><td>L</td><td>8 bit</td></tr><tr><td>H</td><td>6 bit</td></tr></table>	HSD	bit	L	8 bit	H	6 bit	
HSD	bit									
L	8 bit									
H	6 bit									
23	VLED	P	VLED voltage							
24	PWM	O	PWM signal on this pin for brightness control.							
25	NC	-	No connection							
26	NC	-	No connection							
27	NC	-	No connection							
28	NC	-	No connection							
29	NC	-	No connection							
30	NC	-	No connection							

PS. For further details, please refer to HX8282-A data sheet.

4. Absolute Maximum Rating

AGND = GND = 0V, Ta = 25°C

Item	Symbol	Min	Max	Unit	Remark
Power Voltage	VDD	-0.3	3.96	V	
Operating Temperature	T _{OPR}	-20	70	°C	
Storage Temperature	T _{STG}	-30	80	°C	

Note1: The absolute maximum rating values of this product are not allowed to be exceeded at any times. Should a module be used with any of the absolute maximum ratings exceeded, the characteristics of the module may not be recovered, or in an extreme case, the module may be permanently destroyed.

5. Electrical Characteristics

5.1. Recommended Operating Condition

AGND = GND = 0V, Ta = 25°C

Item	Symbol	Min	Typ.	Max	Unit	Remark
Power Voltage	VDD	2.3	3.3	3.6	V	
Input logic high voltage	V _{IH}	0.7VDD	-	VDD	V	
Input logic low voltage	V _{IL}	0	-	0.3VDD	V	

5.2. Recommended Driving Condition for Backlight

Ta = 25°C

Item	Symbol	Min	Typ.	Max	Unit	Remark
Power supply voltage	V _{BL}	4.75	5	5.25	V	
Power supply current	I _{BL}	0.55	0.579	0.609	mA	
Input&Control Signal	On/off On	V _{ON}	1.5	5	V	
	Off	V _{OFF}		0.8	V	
	Brightness Adjust	Dimming	0	100	%	
	BL_DIM Frequency	F _{PWM}	0.2	20	KHz	
	Pulse Duty Level (BL_DIM)	V _H	1.5	5	V	
		V _L		0.4	V	
Life time		30000			Hrs	

Note 1: Ta means ambient temperature of TFT-LCD module.

Note 2: If the module is driven by high current or at high ambient temperature & humidity condition. The operating life will be reduced.


Note 3: Operating life means brightness goes down to 50% initial brightness. Minimum operating life time is estimated data.


6. Timing Characteristics

6.1. AC Electrical Characteristics

LVDS mode AC electrical characteristics

Item	Symbol	Min.	Typ.	Max.	Unit	Remark
Clock Frequency	RXFCLK	20	-	71	MHz	-
Input Data Skew Margin	TRSKM	500	-	-	ps	VID =400Mv Rxvcm=1.2V RXFCLK=71MHz
Clock High Time	TLVCH	-	$4/(7 * \text{RXFCLK})$	-	ns	-
Clock Low Time	TLVCL	-	$3/(7 * \text{RXFCLK})$	-	ns	-
PLL Wake-up Time	TemPLL	-	-	150	us	-






6. 2.DC Electrical Characteristics

Item	Symbol	Min.	Typ.	Max.	Unit	Remark
Differential Input High Threshold Voltage	R_{XVTH}	-	-	+0.1	V	$R_{XVCM}=1.2V$
Differential Input Low Threshold Voltage	R_{XVTL}	-0.1	-	-	V	
Input Voltage Range (Singed-end)	R_{XVIN}	0	-	$V_{DD}-1.2+ VID /2$	V	-
Differential Input Common Mode Voltage	R_{XVCM}	$ VID /2$	-	$V_{DD}-1.2$	V	-
Differential Input Voltage	$ VID $	0.2	-	0.6	V	-
Differential Input Leakage Current	R_{Vxliz}	-10	-	+10	μA	-
LVDS Digital Operating Current	I_{ddLVDS}	-	15	30	mA	$F_{clk}=65MHz$ $V_{DD}=3.3V$
LVDS Digital Stand-by Current	I_{stLVDS}	-	10	50	μA	Clock&all Functions are stopped

Single-end Signals



6. 3.Timing

DE mode

Item	Symbol	Min.	Typ.	Max.	Unit
DCLK Frequency	fclk	40.8	51.2	67.2	MHz
Horizontal Display Area	thd	1024			DCLK
HSD Period	th	1114	1344	1400	DCLK
HSD Banking	thb+thfp	90	320	376	DCLK
Vertical Display Area	tvd	600			T_H
VSD Period	tv	610	635	800	T_H
VSD Blanking	tvbp+tvfp	10	35	200	T_H

HV mode

Horizontal timing



Item	Symbol	Min.	Typ.	Max.	Unit
DCLK Frequency	fclk	44.9	51.2	63	MHz
Horizontal Display Area	thd	1024			DCLK
HSD Period	th	1200	1344	1400	DCLK
HSD Pulse Width	thpw	1	-	140	DCLK
HSD Back Porch	thbp	160			T_H
HSD Front Porch	thfp	16	160	216	T_H

Vertical timing

Item	Symbol	Min.	Typ.	Max.	Unit
Vertical Display Area	tv _d	600			DCLK
VSD Period	tv	624	635	750	DCLK
VSD Pulse Width	tv _{pw}	1	-	20	DCLK
VSD Back Porch	tv _{bp}	23			T _H
VSD Front Porch	tv _{fp}	1	12	127	T _H

6.4.Data input format

LVDS mode data input format




6. 5.Power ON/OFF Sequence

To prevent the device damage from latch up, the power on/off sequence shown below must be followed.


Power on: VDD, GND→AVDD, AGND→V1 to V14

Power off: V1 to V14→AVDD, AGND→VDD, GND

HX8282-A01 has a power on/off sequence control function. In order to prevent IC from power on reset fail, the rising time (TPOR) of the digital power supply VDD should be maintained within the given specifications. Please refer to "AC Characteristics" for more detail on timing.



Power on timing sequence



Power off timing sequence

Note: Low level=3FH, when NBW=L (Normally white)
Low level=00H, when NBW=H (Normally black)

7. Optical Characteristics


Item		Symbol	Condition	Min	Typ	Max	Unit	Remark
View Angles		θT	$CR \geq 10$	-	85	-	Degree	Note 2
		θB		-	85	-		
		θL		-	85	-		
		θR		-	85	-		
Contrast Ratio		CR	$\theta = 0^\circ$	-	800	-		Note 1 Note 3
Response Time		$T_{ON}+T_{OFF}$	25°C	-	30	40	ms	Note 1 Note 4
Chromaticity	W_x	x		-0.03	(0.307)	+0.03		Note 1 Note 5
	W_y	y			(0.338)			
	R_x	x			(0.605)			
	R_y	y			(0.336)			
	G_x	x			(0.297)			
	G_y	y			(0.552)			
	B_x	x			(0.139)			
	B_y	y			(0.132)			
Uniformity		U		75	-	-	%	Note 5
Luminance		L		-	370	-	cd/m ²	Note 1 Note 5

Test Conditions:

1. VDD = 3.3 V, the ambient temperature is 25°C.
2. The test systems refer to Note 2.

Note1: Definition of optical measurement system.


The optical characteristics should be measured in dark room. After 5Minutes operation, the optical properties are measured at the center point of the LCD screen. ALL input terminals LCD panel must be ground when measuring the center area of the panel.



Item	Photo detector	Field
Contrast Ratio	CS1000	1°
Luminance		
Lum Uniformity		
Chromaticity	CS1000	
Response Time	DMS703	-

Note2: Definition of viewing angle range and measurement system.

Viewing angle is measured at the center point of the LCD by CONOSCOPE (DMS703)



Note3: Definition of contrast ratio

White state ":The state is that the LCD should drive by Vwhite.


$$\text{Contrast ratio(CR)} = \frac{\text{Luminance measured when LCD is on the "White" state}}{\text{Luminance measured when LCD is on the "Black" state}}$$

"Black state ":The state is that the LCD should drive by Vblack.

Vwhite: To be determined Vblack: To be determined


Note4: Definition of Response time

The response time is defined as the LCD optical switching time interval between "White"state and "Black" state. Rise time (T_{ON})is the time between photo detector output intensity changed from 90% to 10%.And fall time (T_{OFF})is the time between photo detector output intensity changed from 10% to90%.



Note5: Definition of color chromaticity (CIE1931)
Color coordinates measured at center point of LCD.

Note6: Definition of Luminance Uniformity
Active area is divided into 9 measuring areas(Refer Fig.2).Every measuring point is placed at the center of each measuring area.
Luminance Uniformity (U)= L_{min}/L_{max}
L-Active area length W-Active area width



L_{max} : The measured Maximum luminance of all measurement position.
 L_{min} : The measured Minimum luminance of all measurement position.

Note7: Definition of luminance: Measure the luminance of white state at center point.

8. Environmental/Reliability Test

No.	Test Item	Test Condition	Inspection after test
1	High Temperature Storage	80±2℃/240 hours	Inspection after 2~4hours storage at room temperature, the sample shall be free from defects: 1.Air bubble in the LCD; 2.Sealleak; 3.Non-display; 4.Missing segments; 5.Glass crack; 6.Current Idd is twice higher than initial value.
2	Low Temperature Storage	-30±2℃/240 hours	
3	High Temperature Operating	70±2℃/240 hours	
4	Low Temperature Operating	-20±2℃/240 hours	
5	Temperature Cycle	-30℃~ 25℃~ 80℃ × 10cycles (30min.) (5min.) (30min.)	
6	Damp Proof Test	40℃±5℃×90%RH/240 hours	
7	Vibration Test	Frequency : 10Hz~55Hz~10Hz Amplitude : 1.5mm, X, Y, Z direction for total 3hours (Packing condition)	
8	Dropping test	Drop to the ground from 1m height, one time,every side of carton. (Packing condition)	
9	ESD test	Voltage:±8KV R: 330Ω C: 150pF Air discharge, 10time Voltage:±6KV R: 330Ω C: 150pF Contact discharge, 10time	

Remark:

1. The test samples should be applied to only one test item.
2. Sample size for each test item is 5~10pcs.
3. For Damp Proof Test, Pure water(Resistance> 10MΩ) should be used.
4. In case of malfunction defect caused by ESD damage, if it would be recovered to normal state after resetting, it would be judge as a good part.
5. Failure Judgment Criterion: Basic Specification, Electrical Characteristic, Mechanical Characteristic, Optical Characteristic.
6. Please use automatic switch menu(or roll menu) testing mode when test operating mode.

9. Packing Drawing

CUSTOMER'S APPROVED:

DATE: 2020.10.28

PAGE: 1/1

PRODUCT PART NO.:YTCA10TLAK-04-100N




PACKING TYPE: BY EPE TRAY(TA10TLAK-04-100A)

PACKLING ORDER:

1) Putting 2 pcs Modules on each EPE tray.

2) Putting 6 pcs EPE trays together with EPE paper on the top of EPE tray.




3) Assembling the boards and the tray together with adhesive tape



4) Putting in the inner small carton (TYPE:H82)

5) Putting 5 small cartons into one outcarton

6) Packing finished



Note: 2 pcs in a tray, 6 trays in a inner carton, 5 inner cartons in a out carton, so 2x6x5=60pcs/Outcarton
Dimension (Small carton): 385*325*87mm Dimension (Out carton): 394*344*470mm

NO. YTCA10TLAK-04-100N

Ver. 1

Drw:

Chk:

Apv:

ANSHAN YES OPTOELECTRONICES DISPLAY CO., LTD

10. Standard Specifications For Product Quality

10.1. Manner of test:

10.1.1 The test must be under 40W fluorescent light, and the distance of view must be at 35 ± 5 cm

10.1.2 Room temperature $25 \pm 5^{\circ}\text{C}$ Humidity: $(65 \pm 5)\% \text{RH}$.

10.1.3 If the product is uneven and bright spot, use 2%ND filter to check and confirm. Not visible, OK.

10.1.4 Inspection Angle:

The vision of inspector should be perpendicular to the surface of the Module.

10.1.5 Inspection time :

Perceptibility Test Time: 20 seconds max.

10.2. Quality specification


It shall be based on GB2828, inspection level II.

	IETM	CHECK LEVEL	AQL
MAJOR (MA)	1. Liquid crystal leakage 2. Wrong polarizer 3. Outside dimension 4. Bright dot, Dark dot 5. Display abnormal 6. Glass crack	II	0.25
MINOR (MI)	1. Spot Defect (Including black spot, white spot, pinhole, foreign particle, bubbles, hurt) 2. Fragment 3. Line Defect (Including black line, white line, scratch) 4. Incision defect 5. Newton's ring 6. Other visual defects	II	1.0

10.3 Definition of area

10.3.1 I area: viewing area


II area: outside viewing area



10.4. Standard of appearance test for I area: (unit: mm)



NOTE : Defect ignore for II area.







10.4.1 Bright/Dark Dots explain

Name	Explain	Definition
Bright dot	Dots appear bright and unchanged in size in which LCD panel is displaying under black pattern. 	The definition of dot: The size of a defective dot over 1/2 of single pixel dot is regarded as one defective dot . Note: One pixel consists of 3 sub-pixels, including R,G, and B dot. (Sub-pixel = Dot)
Dark dot	Dots appear dark and unchanged in size in which LCD panel is displaying under pure red, green, blue pattern. 	
Adjacent Dot	Adjacent two sub-pixel are defect (define two dot defect)	

10.4.2 Inspection standard

10.4.2 Inspection standard

No	Items	Criterion				Checking manner	Defect classes
1	Bright/dark dot (亮、暗点)	LCD≤4.3"	4.3" < LCD < 7"	7"≤LCD≤12"	LCD > 12"	Checking with eyes	MAJ
		Bright dot : N≤2 Dark dot : N≤3 Total : N≤4	Bright dot : N≤3 Dark dot : N≤4 Total : N≤6	Bright dot : N≤4 Dark dot : N≤5 Total : N≤8	Bright dot : N≤5 Dark dot : N≤6 Total : N≤10		
		The distance between the two defect dots shall be greater than 5mm The distance between two defect dots above 7 inches shall be more than 10 mm					
		Note: Adjacent dot defect N≤0					
2	Spot defects (black and white spot, pinhole, foreign matter, dent, backlight foreign matter)	D≤0.15 Ignore 0.15 < D≤0.3 N≤3 0.3 < D N=0	D≤0.2 Ignore 0.2 < D≤0.5 N≤4 0.5 < D N=0	D≤0.2 Ignore 0.2 < D≤0.5 N≤5 0.5 < D N=0	D≤0.2 Ignore 0.2 < D≤0.5 N≤6 0.5 < D N=0	Checking with eyes	MIN
	 D=(X+Y)/2						
3	Bubble  D=(X+Y)/2	D≤0.2 Ignore 0.2 < D≤0.5 N≤3 0.5 < D N=0	D≤0.2 Ignore 0.2 < D≤0.5 N≤4 0.5 < D N=0	D≤0.2 Ignore 0.2 < D≤0.5 N≤5 0.5 < D N=0	D≤0.2 Ignore 0.2 < D≤0.5 N≤6 0.5 < D N=0		

No	Items	Criterion				Checking manner	Defect classes
4	Line defects(black and white line, backlight foreign matter etc.) 	LCD≤4.3"	4.3" < LCD < 7"	7"≤LCD≤12"	LCD > 12"	Checking with eyes	MIN
		W≤0.03 Ignore 0.03 < W≤0.06 L≤5 N≤3 W> 0.06 L> 5 N=0	W≤0.03 Ignore 0.03 < W≤0.1 L≤5 N≤4 W> 0.1 L> 5 N=0	W≤0.03 Ignore 0.03 < W≤0.1 L≤5 N≤5 W> 0.1 L> 5 N=0	W≤0.03 Ignore 0.03 < W≤0.1 L≤5 N≤6 W> 0.1 L> 5 N=0		
5	Scratch 	W≤0.03 Ignore 0.03 < W≤0.2 1.0 < L≤ 5.0 N≤3 W> 0.2 L> 5 N=0	W≤0.03 Ignore 0.03 < W≤0.2 1.0 < L≤ 5.0 N≤4 W> 0.2 L> 5 N=0	W≤0.03 Ignore 0.03 < W≤0.2 1.0 < L≤ 5.0 N≤5 W> 0.2 L> 5 N=0	W≤0.03 Ignore 0.03 < W≤0.2 1.0 < L≤ 5.0 N≤6 W> 0.2 L> 5 N=0	Checking with eyes	MIN
6	Display abnormal	Not allowed				Checking with eyes	MAJ
7	Outside dimension	Accord with drawing				Calipers	MAJ
8	Glass crack	Not allowed				Checking with eyes	MAJ
9	Leak	Not allowed				Checking with eyes	MAJ
10	Comer fragment 	X≤3 Y≤3 Z≤T Ignore Note : 1、no hurt identifying 、wire、 seal 2、 T: Glass thickness X: Length Y: Width Z: thickness				Checking with eyes	MIN
11	Side fragment 	Y≤1 Z≤T Ignore Note : 1、no hurt identifying 、wire、 seal 2、 T : Glass thickness X: Length Y: Width Z: thickness				Checking with eyes	MIN
	Step fragment 	Y≤1 and Y≤1/4 L				Checking with eyes	MIN
	Incision defect 	Y≤1 and accord with outside dimension				Checking with eyes	MIN

11. Precautions for Use of LCD Modules

11.1 Handling Precautions

- (1) The display panel is made of glass and polarizer. As glass is fragile. It tends to become or chipped during handling especially on the edges. Please avoid dropping or jarring. Do not subject it to a mechanical shock by dropping it or impact.
- (2) If the display panel is damaged and the liquid crystal substance leaks out, be sure not to get any in your mouth. If the substance contacts your skin or clothes, wash it off using soap and water.
- (3) Do not apply excessive force to the display surface or the adjoining areas since this may cause the color tone to vary. Do not touch the display with bare hands. This will stain the display area and degraded insulation between terminals (some cosmetics are determined to the polarizer).
- (4) The polarizer covering the display surface of the LCD module is soft and easily scratched. Handle this polarizer carefully. Do not touch, push or rub the exposed polarizer with anything harder than an HB pencil lead (glass, tweezers, etc.). Do not put or attach anything on the display area to avoid leaving marks on. Condensation on the surface and contact with terminals due to cold will damage, stain or dirty the polarizer. After products are tested at low temperature they must be warmed up in a container before coming in contact with room temperature air.
- (5) If the display surface becomes contaminated, breathe on the surface and gently wipe it with a soft dry cloth. If it is heavily contaminated, moisten cloth with one of the following solvents
 - Isopropyl alcohol
 - Ethyl alcohol
 - Do not scrub hard to avoid damaging the display surface.
- (6) Solvents other than those above-mentioned may damage the polarizer. Especially, do not use the following.
 - Water
 - Ketone
 - Aromatic solvents

Wipe off saliva or water drops immediately, contact with water over a long period of time may cause deformation or color fading. Avoid contacting oil and fats.
- (7) Exercise care to minimize corrosion of the electrode. Corrosion of the electrodes is accelerated by water droplets, moisture condensation or a current flow in a high-humidity environment.
- (8) Install the LCD Module by using the mounting holes. When mounting the LCD module make sure it is free of twisting, warping and distortion. In particular, do not forcibly pull or bend the I/O cable or the backlight cable.
- (9) Do not attempt to disassemble or process the LCD module.
- (10) NC terminal should be open. Do not connect anything.
- (11) If the logic circuit power is off, do not apply the input signals.
- (12) Electro-Static Discharge Control, Since this module uses a CMOS LSI, the same careful attention should be paid to electrostatic discharge as for an ordinary CMOS IC. To prevent destruction of the elements by static electricity, be careful to maintain an optimum work environment.
 - Before remove LCM from its packing case or incorporating it into a set, be sure the module and your body have the same electric potential. Be sure to ground the body when handling the LCD modules.
 - Tools required for assembling, such as soldering irons, must be properly grounded. make certain the AC power source for the soldering iron does not leak. When using an electric screwdriver to attach LCM, the screwdriver should be of ground potentiality to minimize as much as possible any transmission of electromagnetic waves produced sparks coming from the commutator of the motor.
 - To reduce the amount of static electricity generated, do not conduct assembling and other work under dry conditions. To reduce the generation of static electricity be careful that the air in the work is not too dried. A relative humidity of 50%-60% is recommended. As far as possible make the electric potential of your work clothes and that of the work bench the ground potential.

The LCD module is coated with a film to protect the display surface. Exercise care when peeling off this protective film since static electricity may be generated.

- (13) Since LCM has been assembled and adjusted with a high degree of precision, avoid applying excessive shocks to the module or making any alterations or modifications to it.
- Do not alter, modify or change the shape of the tab on the metal frame.
 - Do not make extra holes on the printed circuit board, modify its shape or change the positions of components to be attached.
 - Do not damage or modify the pattern writing on the printed circuit board.
 - Absolutely do not modify the zebra rubber strip (conductive rubber) or heat seal connector.
 - Except for soldering the interface, do not make any alterations or modifications with a soldering iron.
 - Do not drop, bend or twist LCM.

11.2 Storage Precautions

When storing the LCD modules, the following precaution is necessary.

- (1) Store them in a sealed polyethylene bag. If properly sealed, there is no need for the dessicant.
- (2) Store them in a dark place. Do not expose to sunlight or fluorescent light, keep the temperature between 0°C and 35°C.
- (3) The polarizer surface should not come in contact with any other objects. (We advise you to store them in the container in which they were shipped).

11.3 Others


- (1) Liquid crystals solidify under low temperature (below the storage temperature range) leading to defective orientation or the generation of air bubbles (black or white). Air bubbles may also be generated if the module is subject to a low temperature.
- (2) If the LCD modules have been operating for a long time showing the same display patterns, the display patterns may remain on the screen as ghost images and a slight contrast irregularity may also appear. A normal operating status can be regained by suspending use for some time. It should be noted that this phenomenon does not adversely affect performance reliability.
- (3) To minimize the performance degradation of the LCD modules resulting from destruction caused by static electricity etc., exercise care to avoid holding the following sections when handling the modules.
 - Exposed area of the printed circuit board.
 - Terminal electrode sections.

11.4 USING LCD MODULES

Installing LCD Modules

The hole in the printed circuit board is used to fix LCM as shown in the picture below. Attend to the following items when installing the LCM.


- (1) Cover the surface with a transparent protective plate to protect the polarizer and LC cell.



- (2) When assembling the LCM into other equipment, the spacer to the bit between the LCM and the fitting plate should have enough height to avoid causing stress to the module surface, refer to the individual specifications for measurements. The measurement tolerance should be 0.1mm.

Precaution for assemble the module with BTB connector:

Please note the position of the male and female connector position, don't assemble or assemble like the method which the following picture shows



Precaution for soldering to the LCM

	Hand soldering	Machine drag soldering	Machine press soldering
No ROHS Product	290 C~350 C. Time :3-5S.	330 C ~350 C. Speed : 4-8mm/s.	300 C~330C. Time : 3-6S. Press: 0.8~1.2Mpa
ROHS Product	340 C~370 C. Time:3-5S.	350 C ~370 C. Time : 4-8 mm/s.	330 C~360C. Time : 3-6S. Press: 0.8~1.2Mpa

- (1) If soldering flux is used, be sure to remove any remaining flux after finishing to soldering operation. (This does not apply in the case of a non-halogen type of flux.) It is recommended that you protect the LCD surface with a cover during soldering to prevent any damage due to flux spatters.
- (2) When soldering the electroluminescent panel and PC board, the panel and board should not be detached more than three times. This maximum number is determined by the temperature and time conditions mentioned above, though there may be some variance depending on the temperature of the soldering iron.
- (3) When remove the electroluminescent panel from the PC board, be sure the solder has completely melted, the soldered pad on the PC board could be damaged.

Precautions for Operation

- (1) It is an indispensable condition to drive LCD's within the specified voltage limit since the higher voltage then the limit cause the shorter LCD life. An electrochemical reaction due to direct current causes LCD's undesirable deterioration, so that the use of direct current drive should be avoided.
- (2) Response time will be extremely delayed at lower temperature than the operating temperature range and on the other hand at higher temperature LCD's show dark color in them. However those phenomena do not mean malfunction or out of order with LCD's, which will come back in the specified operating temperature.
- (3) If the display area is pushed hard during operation, the display will become abnormal. However, it will return to normal if it is turned off and then back on.
- (4) A slight dew depositing on terminals is a cause for electro-chemical reaction resulting in terminal open circuit. Usage under the maximum operating temperature, 50%RH or less is required.
- (5) Input each signal after the positive/negative voltage becomes stable.
- (6) Please keep the temperature within specified range for use and storage. Polarization degradation, bubble generation or polarizer peel-off may occur with high temperature and high humidity.

Safety

- (1) It is recommended to crush damaged or unnecessary LCDs into pieces and wash them off with solvents such as acetone and ethanol, which should later be burned.
- (2) If any liquid leaks out of a damaged glass cell and comes in contact with the hands, wash off thoroughly with soap and water.

11.5The disposal of waste

For waste disposal, our recommendations are as follows, please refer to your company, and the relevant provisions of the state laws and regulations of the act accordingly

1. Packing materials disposal for our packaging (carton/PS tray/EPE tray/PET tray)
 - 1) Our company used to recycle and reuse materials, packing materials can be you just need to transfer to material recycling companies
2. Our scrap module can't be recycled for reuse, so please dispose of:
 - 1) Our scrap module can't be recycled for reuse, products and components are "served" can lead to accidents
 - 2) Our scrap can be transfer to material recycling companies, dismantling, to ensure that scrap in relatively advanced technology products, environmental protection measures of relatively perfect environment for processing.
3. WEEE order must be executed in product scrap.

12. Prior Consult Matter

1. (1) For YES standard products, we keep the right to change material, process...for improving the product property without notice on our customer.
(2) For OEM products, if any change needed which may affect the product property, we will consult with our customer in advance.
2. If you have special requirement about reliability condition, please let us know before you start the test on our samples.

13. Factory

FACTORY NAME: YES OPTOELECTRONICS DISPLAY CO.,LTD

FACTORY ADDRESS: No.288 Yueling Road Anshan, Liaoning, P.R.CHINA

FACTORY PHONE: 86-412-5211859 FAX: 86-412-5211729